



Mount all grid stopper resistors direct at tube sockets!

- V1: 7025 (low noise)
- V3, V6: 12AT7
- V2, V4, V5: 12AX7/ECC83
- V7, V8: 6V6 GT-STR
- V9: 5AR4 / GZ 34
- Relais FTR 12V/12mA 2xU
- Conrad 629469

SF 22 Tube Amp

Clean channel based on Fender Deluxe Reverb AB763 (1965)
 Sigi Flamisch V3g 28.02.2018

TR 1: TAD 125P33A P=70W
 red/blk: 240V, grn/blk: 230V, blk/ye: 220V
 ye-ye: 5V/3A, red-red/ye: 325V/0,14A
 red-blu: 52V/0,14A, grn-grn: 6,3V/4A

*) Bias Meas.
 1mA=1mA
 TAD 6V6 GT:
 set Icat/Bias to ~ 20..22 mA
 P_{vmax}=14W
 I_{screen}=2mA!
 V7, V8 paired!

All AC Voltages measured peak (Vs) with all Pots @ .5"

TR 2:
 TAD 125A1A
 2x6V6GT auf 8 Ohm

