
Par. IP Send
6,35mm Jack
Send Level
5k lin
IPS2
1u
220
C1
R3
N3b
+12V (3x)
-12V (3x)
IPS1
K2a
IP off
1k
220
on PCB-B
R4 100k
Par. IP Return
IPR1
C2 1u
R5 22k
N2a
V= -20...+20dB
on PCB-A
R8 10k
N3a
10k R7
Phase
0°
180°
200k lin
RPot
22k R6
Ret Level
IPR2
C7 150n
R9 1M
470p 1M
IN (FRONT)
1Vs
1n Bass Cut
(STILL-GELEGT!)
IN (BACK. SIDE)
Uph 9V DC @ Ring
9V DC ext.
47u
100n
4k7
H3 Uph gn
V1A
V1B
V2A
V2B
220p
25Vs
220k
100k 0,5W
47n 600V
216V 1mA V=25x
1,5V
1M
100p
330p
1n fgu
10k
1M
1u fgu
1k5
Ovd Gain
250k log
33n 600V
33k
6n8
2x ZD1 2V4 (1,5V)
25n
620p
Hi+
Ovd Trim
K3a
3M3
4Vs
1Vs
10p
to RSND
100n
2,2u
alle 600V
250p
40Vs
250k log
0,6Vs
Treb
47n
Bass
Mid
K1a
25k lin
1M log
Vol
(Reverb return) from RR
1n 630V
22u 25V bip.
Mount all grid stopper resistors direct at tube sockets!
RSND
470p C8
N2b
SEND
RETURN
RPIN
RPOUT
Rev Pan 050394
isolated!
4k7 R11
1n
22u 25V bip.
C9
100
R12
R10
R13 10k
R14 22k
N1b
R16 68k
C12 47p
3k3 R15
bip. 22u 25V C10
C11 22u
RRET
5n6
1k5
25k lin
Reverb
470k
RR
FootSw
Sw3 (off=clean or FootSw)
FSW
OVD
K1 ON
K2 ON
K1 not used
K1,K3: 12V
R2 4k7
R1 4k7// 3k3
K2
K1
K3
1N4007
D7
D8
ye H2
red H1
IP off
Ovd
-12V
Relais FTR-B
12V/12mA 2xU
Rcu= 1k
Conrad 629469
F1 1A T
2A/400V
ACA
5V AC
ACB
10W DC-DC-Conv. JCA1005D02
Rect
CS1 1000u 35V
22,23
9,16
2,3
14
11
+12V
max.420mA
CS2 1u
CS3 1u
CS4 22u 25V
4xSiD
CS5 22u 25V
+9V (not used)
GND
max.420mA
-12V
Phantom, OpAmp and Relay Voltages
50u 100V
(ca. -63 V)
UBI-OUT (Bias) ca. -43,5 V
D1 1N4007
470 1W
R3
CS6
10k R1
UBI-IN
ACA
5V/3A AC
ACB
240V
230V
220V
red/blk
grn/blk
ye/blk
ye
red
red/blu
red/ye
2x325V AC
RED1
RED2
1N4007 D1
D2
gr
40u 500V *)
C1
Rg=375
1k/3W
1k5/3W
Ir = 45mA
ws
100k 2W
+440 V
+420 V
+416 V
+360 V
+320 V
(B+)
R3 470/2W
RDC
R4 6k8/2W
RCB
R5 10k/2W
RBA
C3
C4
C5
C6
100u 500V
20u 500V *)
20u 500V *)
22u 500V
*) ELKO 40+3x20uF
L1
1A T
N
PE
230V AC
Pilot Light
Ksp
blk
Sw1
POWER
VDR 250
TR 1
TR 1: TAD 125P33A P=70W
red/blk: 240V, grn/blk: 230V, blk/ye: 220V
ye-ye: 5V/3A, red-red/ye: 325V/0,14A
red-blu: 52V/0,14A, grn-grn: 6,3V/4A
grn
V4
V5
2x100 1% 1W
6,3V AC (Heaters) (6,0V)
3x V1..V3
Speaker protection relay Ksp: Schrack RT14230 230V/12A/1U
A1
A2
12
14
11
N1...N3: TL 072 or NE5532 or equival.
A (NO)
W (COM)
R (NC)
Relay DPDT
Metallfilm!
bottom (wiring) view!
6V6 GT
7025 / 12AX7 / 12AT7 / ECC81 / ECC 83
V1, V2: 7025 / 12AX7 / ECC83
V3: 12AX7 / ECC83 or 12AT7 / ECC81
V4,V5: 6V6 GT-STR
PRT/DLX 22
Output stage based on Fender AB763 (1965)
DI Siegfried Flamisch
V1.8 03.08.2026
82k 0,5W
100k 0,5W
218V
209V
100n 600V
12AT7 / ECC81
V3
22W/8 Ohm = 18,7 Vs
10W/8 Ohm = 12,5 Vs
Jensen Jet Tornado 10" 8 Ohm
SPEAKER
Jack 6,3mm 8 Ohm
470
1M
22k
47
100n
2 x 6V6GT-STR
420V
V4
V5
1k5
470 3W
1R *)
Pin1 V4
Pin1 V5
Pin6 V4,5
TR 2
bl blau
grün gn
gelb ye
schwarz bk
rd rot
bn braun
rot
R_GK 680
Ksp
1k
ge
gr
*) Bias Meas. 1mV=1mA
TAD 6V6 GT: set I to ~20 mA Pvmax=14W Iscreen~2mA!
V4 V5 paired!
TR 2: TAD 125A1A 2x6V6GT auf 8 Ohm